

## making connections beautifully

Decorative Wiring Accessories • Smart Lighting Control • Wireless Audio

## **7G2RBT22**

## Hartland G2 | HARTLAND G2 RANGE | Toggle Switches

| Item Image  | Wiring  | Dimensions                            |
|---|---|---------------------------------------|
|   | Alternative 2 very switching                          | Hemilton HARTLAND G2 T22 2 Way Toggle |
| Primary Range   | Hartland G2   |                                       |
| Insert Type   | 2 gang 20AX 2 Way Toggle                              |                                       |
| Insert Colour   | Richmond Bronze                                       |                                       |
| EAN13 Barcode   | 5051164003968   |                                       |
| Commodity Code  | 85363030  |                                       |
| Luckins TSI   | 407520044   |                                       |
| Dimensions(Nominal)                                     | Single: Height = 87.4mm Width = 87.4mm Depth = 4.65mm |                                       |
| Switched Poles  | Single  |                                       |
| Current Rating  | 20AX  |                                       |
| Voltage   | 220/250V AC   |                                       |
| Maximum Load  | 20 Amp inductive                                      |                                       |
| Mains Frequency   | 50Hz  |                                       |
| IP Rating   | IP2XD   |                                       |
| Contact Gap Minimum                                     | 3mm   |                                       |
| Terminal Capacity 1                                     | 5x1mm <sup>2</sup>                                    |                                       |
| Terminal Capacity 2                                     | 4x1.5mm <sup>2</sup>                                  |                                       |
| Terminal Capacity 3                                     | 2x2.5mm <sup>2</sup>                                  |                                       |
| Terminal Capacity 4                                     | 2x4mm² Multi-strand                                   |                                       |
| Terminal Capacity 5                                     | lx6mm²  |                                       |
| Earth Terminal Capacity 1                               | 6x1mm <sup>2</sup>                                    |                                       |
| Earth Terminal Capacity 2                               | 5x1.5mm <sup>2</sup>                                  |                                       |
| Earth Terminal Capacity 3                               | 3x2.5mm <sup>2</sup>                                  |                                       |
| Earth Terminal Capacity 4                               | 2x4mm² Multi-strand                                   |                                       |
| Earth Terminal Capacity 5                               | 1x6mm²  |                                       |
| Product Class 1   | Must be earthed                                       |                                       |
| Ambient Operating Temperature                           | -5° to +40°C  |                                       |
| Recommended Location                                    | Internal Use Only                                     |                                       |
| Maximum Installation Altitude                           | 2000m   |                                       |
| Standard/Approval                                       | BS EN 60669-1   |                                       |
| 7G2RBT22 - Hartland G2 Richmond Bronze 2 gang 20AX 2 Wa | ay Toggle Richmond Bronze                             |                                       |



Decorative Wiring Accessories • Smart Lighting Control • Wireless Audio

Registered in London No. 941624 VAT Registration No. 222 6607 84

7G2RBT22 - Hartland G2 Richmond Bronze 2 gang 20AX 2 Way Toggle Richmond Bronze

## **7G2RBT22** Hartland G2 | HARTLAND G2 RANGE | Toggle Switches It is the policy of the company to All products listed conform to current All accessories are manufactured improve products as part of our British or European standard and the under an accredited BS EN ISO 9001: development programme. Therefore, product information is correct at the 2015 Quality Management System. we reserve the right to alter designs time of going to press. and dimensions without prior notice. Illustrations and diagrams are Due to manufacturing processes we reproduced within the limitations of Correct as at 30 April 2022 09:05 AM cannot guarantee an exact colour reproduction and printing process and match and shadings of of certain E&OE are not binding. finishes. R Hamilton & Co Ltd, Unit 10 Carrick Business Centre, 4-5 Bonville Road, Brislington, Bristol, BS4 5NZ T: +44 (0)1747 860088 E: info@hamilton-litestat.com www.hamilton-litestat.com Registered Office 1 Rushmills, Bedford Road, Northampton NN4 7YB